



# 正基科技股份有限公司



## AP12275\_M2

### Evaluation Board User Manual

Address:

6F., No. 23, Huanke 1st Rd., Zhubei City, Hsinchu County 302047, Taiwan

Website: <http://www.ampak.com.tw/>





# Revision

Revision	Date	Description	Revised By
0.1	2024/09/27	Initial released	Gary



# Contents

<b>Revision .....</b>	<b>1</b>
<b>1. EVB Introduction .....</b>	<b>2</b>
<b>2. WiFi Function Verification Step .....</b>	<b>3</b>
2.1 WiFi SDIO .....	3
2.2 SDIO Hardware Setup .....	4
2.3 WiFi Software Setup .....	5
<b>3. Bluetooth Function Verification Step.....</b>	<b>6</b>

# 1. EVB Introduction

AP12275\_M2 Evaluation board (EVB) likes as figure1. That is designed for IEEE802.11 a/b/g/n/ac/ax WLAN with integrated Bluetooth application. It is subject to provide a convenient environment for customer's verification on WiFi or Bluetooth function. There are many controller pins and reserved GPIO on Evaluation board which describes as below.




Figure1. Top view of AP12275\_M2 EVB

## Interface highlights:

1. CON1: AP12275\_M2 SIP module.
2. J16: UART interface connects with UART transport board for BT measuring
3. J15: Enable(H) or disable(L) Bluetooth, WiFi function
4. J6: VBAT / WL\_VIO / BT\_VIO for main system I/O power path.
5. J20: 5V DC mini USB input connector.
6. J8: Standard SDIO interfaces for Wi-Fi performance measured.
7. J21: WL\_HOST\_WAKE/BT\_HOST\_WAKE/BT\_DEV\_WAKE/WL\_GPIOs.
8. J7: BT\_PCM interface.
9. J17: CON1 3.3V Power

## 2. WiFi Function Verification Step

### 2.1 WiFi SDIO

Using external pull up resistors depends on the SDIO supply voltage. The resistance range is 30 K $\Omega$ ~40 K $\Omega$  on the four data lines and the CMD line as the following circuitry.




Figure2. WiFi verification connection interface to Host SDIO as using SDIO2.0




Figure3. EVB interface to HOST SDIO 2.0.






Figure4. EVB interface to HOST SDIO 3.0.

- ✧ SDIO 2.0 Hardware Setup:
  - ✧ Pull up voltage should be 3.3V, so make sure R123 is existed.
  - ✧ U7 placed, R56/ R57/ R58/ R59/ R60/ R61/ R62/ R63/ R64/ R65/ R66/ R67 NOP.
- ✧ SDIO 3.0 Hardware Setup:
  - ✧ Pull up voltage should be 1.8V, so make sure R122 is existed.
  - ✧ R56/ R57/ R58/ R59/ R60/ R61/ R62/ R63/ R64/ R65/ R66/ R67 placed, U7 NOP.

## 2.2 SDIO Hardware Setup

- ❖ Refer to Figure2 SDIO pin definition connects the J8 interface of AP12276\_M2 evaluation board to Host SDIO control interface.
- ❖ Using pull high resistors (R108, R109, R110, R111, R112) that resistance is 30Kohm for 1.8V or 3.3V VDDIO pull up voltage. (Pull high resistors are un-necessary if at verification phase.)
- ❖ Connects an external antenna at SMA connector on the evaluation board.
- ❖ Note to the VDDIO voltage level should be the same with GPIO voltage level of Host CPU.

## 2.3 WiFi Software Setup

- ❖ Please follow up software guideline of Ampak official released.



### 3. Bluetooth Function Verification Step




Figure5. Bluetooth verification connection interface to Host UART

#### Hardware Setup:

- ❖ Refer to Figure5 UART pin definition connects the J16 interface of AP12275\_M2 evaluation board to Host UART control interface.
- ❖ Connects an external antenna at SMA connector on the evaluation board.
- ❖ Note to the VDDIO voltage level should be the same as GPIO voltage level of Host CPU.

#### WiFi and Bluetooth software setup:

- ❖ Please follow up software guideline of Ampak official released.